

[0001] This application claims the benefit of the Korean Application No. P2000-65959 filed on November 7, 2000, which is hereby incorporated by reference.

BACKGROUND OF THE INVENTION

Field of the Invention

[0002] The present invention relates to a plasma display panel (PDP) and a driving method thereof, and more particularly, to a PDP and a driving method thereof that can improve luminous efficiency.

Discussion of the Related Art

[0003] A PDP is a display device using visible rays generated from a phosphor when vacuum ultraviolet rays generated by gas discharge excite the phosphor. The PDP is thinner and lighter in weight than a cathode ray tube (CRT) that has been mainly used as a display device. The PDP also enables a large sized screen with high definition.

[0004] Such a PDP includes a plurality of discharge cells, each cell having one pixel on a screen.

[0005] FIG. 1 is a perspective view illustrating a discharge cell of a related art three-electrode alternating current area discharge type PDP.

[0006] Referring to FIG. 1, the discharge cell of the related art three-electrode alternating current area discharge type PDP includes a scan/sustain electrode 12Y, a common sustain electrode 12Z, and an address electrode 20X. The scan/sustain electrode 12Y and the common sustain electrode 12Z are formed on an upper substrate 10, and the address electrode 20X is formed on a lower substrate 18.

[0007] On the upper substrate 10 on which the scan/sustain electrode 12Y and the common sustain electrode 12Z are formed in parallel, an upper dielectric layer 14 and a passivation film 16 are layered. Wall charges generated by a plasma discharge are accumulated in the upper dielectric layer 14. The passivation film 16 prevents the upper dielectric layer 14 from being damaged due to sputtering generated by the plasma discharge and increases secondary electron emission. MgO is generally used as the passivation film 16.

[0008] A lower dielectric layer 22 and a sidewall 24 are formed on the lower substrate 18 on which the address electrode 20X is formed. A phosphor layer 26 is deposited on surfaces of the lower dielectric layer 22 and the sidewall 24.

00009] The address electrode 20X is formed to cross the scan/sustain electrode 12Y and the common sustain electrode 12Z. The sidewall 24 is formed in parallel with the address electrode 20X, so that ultraviolet rays and visible rays generated by a discharge are prevented from leaking out to an adjacent discharge cell. The phosphor layer 26 is excited by the ultraviolet rays generated by the plasma discharge and generates one of red, green, or blue visible rays.

00010] Also, an inert gas for a gas discharge is injected into a discharge space between the upper substrate 10 or the lower substrate 18 and the sidewall 24.

00011] The aforementioned alternating current area discharge type PDP divides one frame into a plurality of sub-fields having different discharge number of times to display gray level of a picture image. Each sub-field includes a reset period for uniformly generating a discharge, an address period for selecting a discharge cell, and a sustain period for displaying gray level in accordance with discharge number of times. For example, if a picture image is displayed in 256 gray levels, a frame period (16.67ms) corresponding to 1/60 sec. is divided into eight sub-fields. Each of the eight sub-fields is divided into a reset period, an address period, and a sustain period. The reset period has the same value in each sub-field. Likewise, the address period has the same value in each sub-field. However, the sustain

a high driving voltage should be applied to the scan/sustain electrode 12Y and the common sustain electrode 12Z. That is, power consumption is increased for the sustain discharge, thereby reducing driving efficiency of the PDP.

[0014] To solve such a problem, a five-electrode alternating current area discharge type PDP as shown in FIG. 3 has been proposed.

[0015] FIG. 3 is a perspective view illustrating a discharge cell of another related art five-electrode alternating current area discharge type PDP.

[0016] Referring to FIG. 3, the related art five-electrode alternating current area discharge type PDP includes first and second trigger electrodes 34Y and 34Z formed at the center of a discharge cell on an upper substrate 30, a scan/sustain electrode 32Y and a common sustain electrode 32Z formed at a peripheral portion of the discharge cell on the upper substrate 30, and an address electrode 42X formed at the center of the lower substrate 40 to be orthogonal to the trigger electrodes 34Y and 34Z, the scan/sustain electrodes 32Y, and the common sustain electrode 32Z. On the upper substrate 30 on which the scan/sustain electrode 32Y, the first trigger electrode 34Y, the second trigger electrode 34Z, and the common sustain electrode 32Z are formed in parallel, an upper dielectric layer 36 and a passivation film 38 are layered. On the lower substrate 40 on which the address electrode 42X is

formed, a lower dielectric layer 44 and a sidewall 46 are formed. A phosphor layer 48 is deposited on surfaces of the lower dielectric layer 44 and the sidewall 46.

[0017] An alternating current pulse is supplied to the trigger electrodes 34Y and 34Z formed at the center of the discharge cell at a narrow distance during the sustain period. The trigger electrodes 34Y and 34Z are used to start a sustain discharge. The alternating current pulse is also supplied to the scan/sustain electrode 32Y and the common sustain electrode 32Z formed at a wider distance at the peripheral portion of the discharge cell during the sustain period. The scan/sustain electrode 32Y and the common sustain electrode 32Z are used to start a plasma discharge between the trigger electrodes 34Y and 34Z and to maintain the plasma discharge. To drive the five-electrode alternating current area discharge type PDP, a waveform shown in FIG. 4 is applied.

[0018] Referring to FIG. 4, in the related art five-electrode alternating current area discharge type PDP, one frame is divided into various sub-fields having different discharge numbers of times to display gray levels of a picture image. Each sub-field includes a reset period for uniformly generating a discharge, an address period for selecting a discharge cell, and a sustain period for displaying gray levels in accordance with discharge numbers of times.

[0019] During the reset period, a reset pulse is supplied to the second trigger electrode Tz so that a reset discharge for initiating the discharge cell occurs. At this time, a direct current voltage is supplied to the address electrode X to prevent an error discharge from occurring.

[0020] During the address period, scan pulses C are sequentially supplied to the first trigger electrode Ty and data pulses Va synchronized with the scan pulses C are supplied to the address electrode X. At this time, an address discharge occurs in the discharge cell to which the data pulses Va are supplied.

[0021] During the sustain period, sustain pulses are alternately applied between the first trigger electrode Ty and the scan/sustain electrode Sy and between the second trigger electrode Tz and the common sustain electrode Sz. At this time, a voltage Vt applied to the trigger electrodes Ty and Tz has a lower level than a voltage Vs applied to the scan/sustain electrode Sy and the common sustain electrode Sz. During the sustain period, a direct current voltage is supplied to the address electrode X to prevent an error discharge from occurring.

[0022] A sustain discharge step will be described in more detail with reference to FIG. 5.

[0023] First, if the sustain pulse is applied to the first trigger electrode Ty, the scan/sustain electrode Sy, the second trigger electrode Tz, and the common sustain electrode Sz, a

00000000-10000000

trigger discharge occurs between the first trigger electrode T_y and the second trigger electrode T_z . Then, a transition discharge occurs between the second trigger electrode T_z and the common sustain electrode S_z or between the first trigger electrode T_y and the scan/sustain electrode S_y . As a result, the trigger discharge generated between the first trigger electrode T_y and the second trigger electrode T_z is transited to the sustain discharge between the scan/sustain electrode S_y and the common sustain electrode S_z . In other words, the sustain discharge occurs between the scan/sustain electrode S_y and the common sustain electrode S_z after the transition discharge occurs. At this time, even if the distance between the scan/sustain electrode S_y and the common sustain electrode S_z is great, a discharge can occur by means of a sustain pulse having a relatively low voltage level due to priming charged particles generated by the transition discharge. Thus, the sustain discharge having a long discharge path can occur while reducing increase of a sustain voltage.

[0024] However, a transition discharge path in the five-electrode alternating current area discharge type PDP is almost half of a sustain discharge path. That is, to generate the transition discharge corresponding to half of the sustain discharge path, a high voltage should be applied to the trigger electrodes T_y and T_z . A strong transition discharge occurs due to

119071-05560

[0028] To achieve these objects and other advantages and in accordance with the purpose of the invention, as embodied and broadly described herein, a PDP according to the present invention includes: a scan/sustain electrode formed at a peripheral portion of a discharge cell; a common sustain electrode formed to oppose the scan/sustain electrode at the peripheral portion of the discharge cell; a first trigger electrode formed to be adjacent to the scan/sustain electrode; and a second trigger electrode formed to be adjacent to the common sustain electrode.

[0029] In another aspect, a PDP according to the present invention includes: a scan/sustain electrode formed at a peripheral portion of a discharge cell; a common sustain electrode formed to oppose the scan/sustain electrode at the peripheral portion of the discharge cell; a first trigger electrode formed to be adjacent to the scan/sustain electrode; and a second trigger electrode formed to be adjacent to the common sustain electrode, the first and second trigger electrodes being formed between the scan/sustain electrode and the common sustain electrode.

[0030] In another aspect, a PDP according to the present invention includes: a first trigger electrode formed at a peripheral portion of a discharge cell; a second trigger electrode formed to oppose the first trigger electrode at the

peripheral portion of the discharge cell; a scan/sustain electrode formed to be adjacent to the first trigger electrode; and a common sustain electrode formed to be adjacent to the second trigger electrode, the scan/sustain electrode and the common sustain electrode being formed between the first and second trigger electrodes.

[0031] In another aspect, a method for driving a PDP according to the present invention includes the steps of: alternately applying a first sustain pulse having a predetermined voltage to a scan/sustain electrode and a common sustain electrode during a sustain period; supplying a second sustain pulse to a first trigger electrode whenever the first sustain pulse is supplied to the scan/sustain electrode and the common sustain electrode; and supplying a third sustain pulse to a second trigger electrode whenever the first sustain pulse is supplied to the scan/sustain electrode and the common sustain electrode.

[0032] The second and third sustain pulses have a lower voltage value than the first sustain pulse.

[0033] The method for driving a PDP further includes the steps of supplying the second sustain pulse having a lower voltage value than the first sustain pulse to the first trigger electrode when the first sustain pulse is supplied to the scan/sustain electrode, and supplying the third sustain pulse

having a lower voltage value than the second sustain pulse to the second trigger electrode when the first sustain pulse is supplied to the scan/sustain electrode.

[0034] The method for driving a PDP further includes the steps of supplying the third sustain pulse having a lower voltage value than the first sustain pulse to the second trigger electrode when the first sustain pulse is supplied to the common sustain electrode, and supplying the second sustain pulse having a lower voltage value than the third sustain pulse to the first trigger electrode when the first sustain pulse is supplied to the common sustain electrode.

[0035] If the second and third sustain pulses have the same voltage value, the second sustain pulse having a lower voltage value than the first sustain pulse is synchronized with the first sustain pulse supplied to the scan/sustain electrode and the common sustain electrode, and is supplied to the first trigger electrode. The third sustain pulse having a lower voltage value than the first sustain pulse is supplied to the second trigger electrode.

[0036] It is to be understood that both the foregoing general description and the following detailed description of the present invention are exemplary and explanatory and are intended to provide further explanation of the invention as claimed.

BRIEF DESCRIPTION OF THE DRAWINGS

[0037] The accompanying drawings, which are included to provide a further understanding of the invention and are incorporated in and constitute a part of this application, illustrate embodiment(s) of the invention and together with the description serve to explain the principle of the invention. In the drawings:

[0038] FIG. 1 is a perspective view illustrating a discharge cell of a related art three-electrode PDP;

[0039] FIG. 2 is a sectional view illustrating a sustain discharge of the PDP shown in FIG. 1;

[0040] FIG. 3 is a perspective view illustrating a discharge cell of a related art five-electrode PDP;

[0041] FIG. 4 illustrates a driving waveform applied to the PDP shown in FIG. 3;

[0042] FIG. 5 is a sectional view illustrating a sustain discharge of the PDP shown in FIG. 3;

[0043] FIG. 6 is a perspective view illustrating a discharge cell of a PDP according to the first embodiment of the present invention;

[0044] FIG. 7 illustrates a driving waveform applied to the PDP shown in FIG. 6 during a sustain period;

[0045] FIG. 8 illustrates a driving waveform applied to the PDP shown in FIG. 6 during a sustain period;

[0046] FIGS. 9 and 10 are sectional views illustrating a sustain discharge of the PDP shown in FIG. 6; and

[0047] FIG. 11 is a perspective view illustrating a discharge cell of a PDP according to the second embodiment of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

[0048] Reference will now be made in detail to the preferred embodiments of the present invention, examples of which are illustrated in the accompanying drawings. Wherever possible, the same reference numbers will be used throughout the drawings to refer to the same or like parts.

[0049] FIG. 6 is a perspective view illustrating a structure of a discharge cell of a PDP according to the first embodiment of the present invention.

[0050] Referring to FIG. 6, the PDP according to the first embodiment of the present invention includes a scan/sustain electrode 52Y and a common sustain electrode 52Z formed at a peripheral portion of a discharge cell on an upper substrate 50, first and second trigger electrodes 54Y and 54Z formed to be adjacent to the scan/sustain electrode 52Y and the common sustain electrode 52Z, and an address electrode 62X formed at the center of a lower substrate 60 to be orthogonal to the first and second trigger electrodes 54Y and 54Z, the scan/sustain electrodes 52Y,

and the common sustain electrodes 52Z. On the upper substrate 50 on which the scan/sustain electrode 52Y, the first trigger electrode 54Y, the second trigger electrode 54Z, and the common sustain electrode 52Z are formed in parallel, an upper dielectric layer 56 and a passivation film 58 are layered. On the lower substrate 60 on which the address electrode 62X is formed, a lower dielectric layer 64 and a sidewall 66 are formed. A phosphor layer 68 is deposited on surfaces of the lower dielectric layer 64 and the sidewall 66.

[0051] Unlike the related art PDP, in the first embodiment of the present invention, the scan/sustain electrode 52Y and the first trigger electrode 54Y are disposed to be adjacent to each other. Also, the common sustain electrode 52Z and the second trigger electrode 54Z are disposed to be adjacent to each other. That is, in the related art PDP, the first and second triggers 34Y and 34Z are formed at the center of the upper substrate 30. While the first and second trigger electrodes 54Y and 54Z of the present invention are disposed to be adjacent to the scan/sustain electrode 52Y and the common sustain electrode 52Z. For example, the scan/sustain electrode 52Y and the common sustain electrode 52Z are formed at a width of 180 μ m while the first and second trigger electrodes 54Y and 52Z are formed at a width of 80 μ m. The scan/sustain electrode 52Y and the first trigger electrode 54Y are formed at a distance of 80 μ m. The common sustain

electrode 52Z and the second trigger electrode 54Z are also formed at a distance of 80 μ m.

[0052] An alternating current pulse is supplied to the trigger electrodes 54Y and 54Z adjacent to the scan/sustain electrode 52Y and the common sustain electrode 52Z during a sustain period. Thus, a trigger discharge occurs between the first trigger electrode and the scan/sustain electrode 52Y and between the second trigger electrode and the common sustain electrode 52Z. The alternating current pulse is also supplied to the scan/sustain electrode 52Y and the common sustain electrode 52Z formed at the peripheral portion of the discharge cell during the sustain period. Thus, a trigger discharge occurs between the first trigger electrode 54Y and the scan/sustain electrode 52Y and between the second trigger electrode 54Z and the common sustain electrode 52Z. Also, the scan/sustain electrode 52Y and the common sustain electrode 52Z are used to maintain a plasma discharge after starting the trigger discharge.

[0053] In the PDP according to the first embodiment of the present invention, one frame is divided into various sub-fields having different discharge number of times to display gray level of a picture image. Each sub-field includes a reset period for uniformly generating a discharge, an address period for selecting a discharge cell, and a sustain period for displaying gray level in accordance with discharge number of times.

[0054] During the reset period, a reset pulse is supplied to the second trigger electrode 54Z so that a reset discharge for initiating the discharge cell occurs. At this time, a direct current voltage is supplied to the address electrode 62X to prevent an error discharge from occurring.

[0055] During the address period, scan pulses are sequentially supplied to the first trigger electrode 54Y and data pulses synchronized with the scan pulses are supplied to the address electrode 62X. At this time, an address discharge occurs in the discharge cell to which the data pulses are supplied.

[0056] During the sustain period, sustain pulses are applied to the first trigger electrode 54Y, the second trigger electrode 54Z, the scan/sustain electrode 52Y, and the common sustain electrode 52Z.

[0057] FIG. 7 is a waveform of the sustain pulses applied to the respective electrodes 52Y, 52Z, 54Y, and 54Z during the sustain period.

[0058] Referring to FIG. 7, the sustain pulses having different voltages are supplied to the scan/sustain electrode Sy, the common sustain electrode Sz, the first trigger electrode Ty, and the second trigger electrode Tz.

[0059] At this time, it is assumed that a trigger discharge occurs when a voltage difference of 230V or greater should be generated between adjacent electrodes, i.e., between the

scan/sustain electrode Sy and the first trigger electrode Ty and between the common sustain electrode Sz and the second trigger electrode Tz. In this case, the sustain period will be described below.

[0060] First, the sustain pulse having a predetermined voltage value Vy (ex, 350V) is applied to the scan/sustain electrode Sy. At this time, the sustain pulse having a lower voltage value Vy1 (ex, 300V) than the sustain pulse applied to the scan/sustain electrode Sy is supplied to the first trigger electrode Ty. The sustain pulse having a lower voltage value Vz1 (ex, 200V) than the sustain pulse applied to the first trigger electrode Ty is supplied to the second trigger electrode Tz. The voltage value Vy of the sustain pulse applied to the scan/sustain electrode Sy is higher by about 50V than the voltage value Vy1 of the sustain pulse applied to the first trigger electrode Ty. Meanwhile, the sustain pulse having a voltage value of 0V is applied to the common sustain electrode Sz. That is, a voltage difference of 50V occurs between the scan/sustain electrode Sy and the first trigger electrode Ty while a voltage difference of 200V occurs between the common sustain electrode Sz and the second trigger electrode Tz.

[0061] If the sustain pulse is applied as above, a voltage difference of wall charges formed in discharge cells selected during the address period is added to the voltage difference

between the common sustain electrode Sz and the second trigger electrode Tz, thereby resulting in that the trigger discharge occurs as shown in FIG. 9. After the trigger discharge occurs between the common sustain electrode Sz and the second trigger electrode Tz, a sustain discharge occurs between the scan/sustain electrode Sy and the common sustain electrode Sz.

[0062] In the related art five-electrode PDP, the trigger discharge and the transition discharge occur before the sustain discharge occurs. However, in the PDP according to the first embodiment of the present invention, the trigger discharge only occurs before the sustain discharge occurs. In other words, since the transition discharge corresponding to half of the sustain discharge path does not occur, discharge efficiency can be improved.

[0063] Afterwards, the sustain pulse having a predetermined voltage value Vz (ex, 350V) is applied to the common sustain electrode Sz. That is, the voltage Vz of the sustain pulse applied to the common sustain electrode Sz is equal to the voltage Vy of the sustain pulse applied to the scan/sustain electrode Sy. After the sustain pulse having a predetermined voltage value Vz is applied to the common sustain electrode Sz, the sustain pulse having a lower voltage value Vy1 (ex, 300V) than the sustain pulse applied to the common sustain electrode Sz is supplied to the second trigger electrode Tz. Meanwhile, the

sustain pulse having a lower voltage value V_{z1} (ex, 200V) than the sustain pulse applied to the second trigger electrode T_z is supplied to the first trigger electrode T_y , and the sustain pulse having a voltage value of 0V is applied to the scan/sustain electrode S_y .

[0064] If the sustain pulse is applied, the wall voltage difference generated by the voltage difference 50V of the sustain pulse previously applied to the scan/sustain electrode S_y and the first trigger electrode T_y are added to the voltage difference 200V of the sustain pulse currently applied to the scan/sustain electrode S_y and the first trigger electrode T_y , thereby resulting in that the trigger discharge occurs as shown in FIG. 10. After the trigger discharge occurs between the scan/sustain electrode S_y and the first trigger electrode T_y , the sustain discharge occurs between the scan/sustain electrode S_y and the common sustain electrode S_z . In the sustain period of the present invention, the sustain pulse is alternately applied to the respective electrodes S_y , S_z , T_y and T_z . Meanwhile, since wall charges are not formed in discharge cells which are not selected in the address period, conditions for discharge are not generated. In other words, since no voltage difference of 230V occurs in the discharge cells which are not selected in the address period, the trigger discharge and the sustain discharge are not generated.

[0065] Meanwhile, in the present invention, a driving waveform of FIG. 8 may be generated.

[0066] Referring to FIG. 8, the sustain pulses having the same voltage value V_y (ex, 350V) are alternately supplied to the scan/sustain electrode S_y and the common sustain electrode S_z , and the sustain pulses having the same voltage value V_{y1} (ex, 200V) are supplied to the first and second trigger electrodes T_y and T_z to synchronize with the sustain pulses applied to the scan/sustain electrode S_y and the common sustain electrode S_z . It is assumed that the sustain pulse having a voltage value of 350V is supplied to the scan/sustain electrode S_y and the sustain pulse having a voltage value of 0V is supplied to the common sustain electrode S_z . In this case, if the sustain pulse having a voltage of 350V is supplied to the scan/sustain electrode S_y , a voltage difference of 100V occurs between the scan/sustain electrode S_y and the first trigger electrode T_y . If the sustain pulse having a voltage of 0V is supplied to the common sustain electrode S_z , a voltage difference of 200V occurs between the common sustain electrode S_z and the second trigger electrode T_z . At this time, the wall charges formed in the discharge cells selected in the address period are added to the voltage of 200V supplied to the second trigger electrode T_z , so that the trigger discharge occurs between the common sustain electrode S_z and the second trigger electrode T_z as shown in FIG. 9. After the trigger

discharge occurs between the common sustain electrode Sz and the second trigger electrode Tz, the sustain discharge occurs between the scan/sustain electrode Sy and the common sustain electrode Sz. Afterwards, the sustain pulse having a voltage value of 350V is supplied to the common sustain electrode Sz and the sustain pulse having a voltage value of 0V is supplied to the scan/sustain electrode Sy. Once the sustain pulse having a voltage value of 0V is supplied to the scan/sustain electrode Sy, the trigger discharge occurs between the scan/sustain electrode Sy and the first trigger electrode Ty as shown in FIG. 10. After the trigger discharge occurs between the scan/sustain electrode Sy and the first trigger electrode Ty, the sustain discharge occurs between the scan/sustain electrode Sy and the common sustain electrode Sz. Actually, the sustain pulse is supplied to the respective electrodes Sy, Sz, Ty, and Tz, so that the sustain discharge occurs. Meanwhile, in the driving waveform according to another embodiment of the present invention as shown in FIG. 8, the sustain pulses always having the same voltage are supplied to the trigger electrodes Ty and Tz. The trigger electrodes Ty and Tz of the PDP in which the driving waveform of FIG. 8 is generated may be added electrically and/or physically to each other.

[0067] FIG. 11 is a perspective view illustrating a discharge cell of a PDP according to the second embodiment of the present invention.

[0068] Referring to FIG. 11, the PDP according to the second embodiment of the present invention includes first and second trigger electrodes 72Y and 72Z formed at a peripheral portion of a discharge cell on an upper substrate 70, scan/sustain electrode 74Y and a common sustain electrode 74Z formed to be adjacent to the first and second trigger electrodes 72Y and 72Z between the first and second trigger electrodes 72Y and 72Z, and an address electrode 82X formed at the center of a lower substrate 80 to be orthogonal to the first and second trigger electrodes 72Y and 72Z. On the upper substrate 70 on which the scan/sustain electrode 74Y, the first trigger electrode 72Y, the second trigger electrode 72Z, and the common sustain electrode 74Z are formed in parallel, an upper dielectric layer 76 and a passivation film 78 are layered. On the lower substrate 80 on which the address electrode 82X is formed, a lower dielectric layer 84 and a sidewall 86 are formed. A phosphor layer 88 is deposited on surfaces of the lower dielectric layer 84 and the sidewall 86.

[0069] Unlike the first embodiment of the present invention, in the second embodiment of the present invention, the scan/sustain electrode 74 and the common sustain electrode 74Z are formed between the first and second trigger electrodes 72Y and 72Z. Other structure and operation according to the second embodiment of the present invention will be equal to the first embodiment of the present invention. That is, in the PDP

according to the second embodiment of the present invention, the driving waveform of FIG. 7 or FIG. 8 may be generated during the sustain period. Meanwhile, in the PDP according to the second embodiment of the present invention, if the driving waveform of FIG. 8 is formed, the trigger electrodes 72Y and 72Z formed in one discharge cell may be added to each other electrically and/or physically. Also, the trigger electrodes 72Y and 72Z formed in one discharge cell may electrically and/or physically be added to the trigger electrodes 72Y and 72Z formed in adjacent discharge cells.

[0070] As described above, the PDP and the driving method thereof according to the present invention have the following advantages.

[0071] The trigger electrodes are formed to be adjacent to the scan/sustain electrode and the common sustain electrode. Once the trigger electrodes are formed to be the scan/sustain electrode and the common sustain electrode, the sustain discharge can be generated by the trigger discharge only during the sustain period. That is, since the sustain discharge can be generated by the trigger discharge which is a fine discharge, a strong sustain discharge contributed to luminance can be generated. Therefore, luminance and luminous efficiency of the PDP can be improved.

[0072] It will be apparent to those skilled in the art than various modifications and variations can be made in the present

invention. Thus, it is intended that the present invention covers the modifications and variations of this invention provided they come within the scope of the appended claims and their equivalents.

RECEIVED
FEB 11 1960